

EECS 861
Homework #9

1. A zero mean WSS random process, $X(t)$ has the following autocorrelation function

$$R_{XX}(\tau) = e^{-100|\tau|}$$

- a. Find $E[X(t)]$
- b. Find the variance of $X(t)$.
- c. Find the effective bandwidth, B_{eff} of $X(t)$.
- d. Find the correlation time τ_c in ms

Let

$$Y = \frac{1}{T} \int_0^T X(\eta) d\eta$$

- e. For $T = 5$ ms find the variance of Y and the ratio of $\text{Var}[X]/\text{Var}[Y]$.
- f. For $T = 2000$ ms find the variance of Y and the ratio of $\text{Var}[X]/\text{Var}[Y]$; then compare the $\text{Var}[Y]$ to the large $B_{\text{eff}}T$ approximation of the of $\text{Var}[Y]$.
- g. For $T = 2000$ ms find $P(Y > 0.05)$

2. Let $X(t) = A \cos(2\pi 1000t)$ where A is a random variable with $E[A] = m$ and $\text{Var}[A] = \sigma^2$.

- a. Find $E[X(t)]$
- b. Find $\langle X(t) \rangle_T = \frac{1}{T} \int_{-T/2}^{T/2} X(t) dt$
- c. Find $\lim_{T \rightarrow \infty} \langle X(t) \rangle_T$
- d. Compare the results from part a and part b.
- e. Repeat a. and d. with $E[A] = 0$ and $\text{Var}[A] = \sigma^2$

3. Explain the concepts of strict sense stationarity and ergodicity.

4. Chapter 3: Problem 3.26

$X(t)$ and $Y(t)$ are two independent WSS random processes with the power spectral density functions shown below-Figure 3.34. Let $Z(t) = X(t)Y(t)$. Sketch the Power Spectral Density of $Z(t)$, and find $S_Z(0)$.




Figure 3.34 Psd functions for Problem 3.26.

5. A zero mean Gaussian WSS random process, $X(t)$ has the following PSD

$$S_X(f) = \frac{1}{500} \Lambda\left(\frac{f}{500}\right)$$

- a. Plot $R_{XX}(\tau)$.
- b. Find $E[X(t)]$
- c. Find $\text{Var}[X(t)]$
- d. Are the random variables $X(t)$ and $X(t-2\text{ms})$ uncorrelated (Yes or No); justify?

e. Are the random variables $X(t)$ and $X(t-2\text{ms})$ statistically independent (Yes or No); justify?

f. What is $P(X(t) > 2 | X(t-2\text{ms}) = 3.1)$?

g. What is the bivariate pdf for the random variables $X(t)$ and $X(t-1\text{ms})$, Specify the pdf, mean vector and covariance matrix.

6. Given the random process given in problem 5, i.e., $X(t)$ has the following PSD

$S_x(f) = \frac{1}{500} \Lambda\left(\frac{f}{500}\right)$. The average of 10 samples which are collected at a sample rate of 500

samples/sec is formed as $Y = \frac{1}{10} \sum_{k=1}^{10} X(t - k\Delta t)$ where $\Delta t = 2 \text{ ms}$

a. Find the variance of Y .

b. How long do you need to sample $X(t)$ (that observe the signal $X(t)$) at a sample rate of 500 samples/sec such that the variance of the time average $\text{Var}[Y] = 0.01$